### **Technical data sheet**

#### 0° socket, protective contact, triple

**Item number: 6120052** 



Power socket, triple 0°, with increased touch protection with screwless terminals, 2-pin, 16 A, 250 V~, with connection terminals to IEC 60884-1.

For installation in Rapid 45 trunking, device installation trunking, service poles, underfloor systems and desk boxes.







Polycarbonate

B.A			 _	_	4_
М	n s	414	м	ы	га

Item number	6120052
Description 1	Socket 0°, triple
Description 2	protective contact
Manufacturer	OBO
Dimension	250V, 10/16A
Colour	Aluminium painted
Material	Polycarbonate
Smallest sales unit	1
Unit of quantity	Piece
Weight	12.2 kg
Weight unit	kg/100 pc.
CO Footprint (GWP) Cradle-to- Gate	0,5597 kg COe / 1 Piece


### **Technical data sheet**

### 0° socket, protective contact, triple





# Dimensions Width 135 mm Height 45 mm



#### Technical data

Cover	Central plate		
Closable	no		
Connection type	Screwless terminal		
Number of units	3		
Number of modules (for modular construction)	0		
Number of switchable sockets	0		
Number of poles	2		
Printed label/coding	Without printing		
Version for	Triple 0°		
Surface version	Matt		
Version for	SCHUKO		
Ejection mechanism	no		
Fastening type	Lock		
Labelling panel	no		
Operating temperature, max.	40 °C		
Operating temperature, min.	-5 °C		
increased touch protection	yes		
Error current protection	no		
For more difficult conditions (according to VDE)	no		
Power reserve	no		
Halogen-free	yes		
Insulated installation	no		
Hinged cover	no		
Coding	no		
Warning light	no		
With on/off switch	no		
With fine-wire fuse	no		
With functional lighting	no		
With orientation lighting	no		
Mounting type	Device installation duct		
Nominal voltage	250 V		
Nominal current	16 A		
Protection rating	Other		
Special power supply	Without special power supply		

## Technical data sheet

0° socket, protective contact, triple

**Item number: 6120052** 



Technical data		
	Socket version	Protective contact
	Socket angle	0°
	Depth	42 mm
	Transparent	no
	Rotated central insert	no
	Approvals	VDE
	Surge protection	no